

HELPY 2W-4G.VoLTE

Autodialer with built-in 4G module




- Up to 32 speaker units
- Built-in 4G module with fallback to 3G and 2G networks
- 2-wire BUS connection
- Configurable via web server and web-app
- Remote monitoring and predictive maintenance









Dimensions: 182 x 123 x 62 mm
Weight: 654 g

Product	Part number	Description
HELPY 2W-4G.VoLTE	5HL-520	HELPY 2W-4G.VoLTE: new-generation dialer in plastic box which includes: <ul style="list-style-type: none">- 4G LTE module- power supply and backup batteries- magnet-base antenna with cable L= 2 m,- alarm and reset pushbutton- 230V power supply cable- LEDs signalling operation status, GSM signal strenght, line status and power supply status
HELPY 2W-4G VOICE AUS	5HL-532	HELPY 2W-4G VOICE AUS: specific version for Australia.
HELPY 2W-4G VOLTE US	5HL-540	HELPY 2W-4G VOLTE US: specific version for North America.
HELPY 2W-4G VOLTE LATAM	5HL-545	HELPY 2W-4G VOLTE LATAM: specific version for Latin America




Main Features	
• Telephone numbers: programmable, up to 24	• Voice prompts: menu with 8 languages, customizable with SW e-stant or micro-SD card
• Supported voice terminals: up to 16 2W speaker units, max 32 with passive handsfree terminals	• 2 Relays: programmable, multi-function
• Digital volume adjustment	• 4 inputs: programmable, multi-function
• Advanced self-diagnosis system	• Alarm ending with or without reset codes
• Voice and data over 4G with fallback to 3G and 2G	• Technological alarms: speaker-unit failure, low battery, battery replacement, power supply failure, diagnostics, auxiliary, stuck pushbutton, speaker/MIC test, LMS funtionality, power supply restore, timer, SIM Card expiring
• Local programming: telephone (DTMF tones), micro SD card, computer with e-stant software and USB serial cable	• Multi-Sharing function: simultaneous notification of the same alarm to different receivers
• Remote programming: app e-stant web, telephone (DTMF tones), computer with e-stant SW (HeControl) and HeGate modem, SMS	• SD Card: extended event log; firmware update; voice messages upload; parameter settings.
• Alarm sending modes: voice, CLI, Esse-ti protocol, P100 protocol, data protocol, SMS, data notifications to webapp	




Handsfree Speaker Units

- **5HV-300**
2W SPEAKER UNIT - Independent digital speaker unit with microphone and loudspeaker. 2-wire BUS connection.
- **5HV-302**
2W SPEAKER UNIT WITH PUSHBUTTON - Independent digital speaker unit with microphone, loudspeaker and emergency button. 2-wire BUS connection.
- **5HV-324**
2W STAINLESS-STEEL SPEAKER UNIT - Complete with microphone, loudspeaker, double-contact emergency pushbutton, pictograms with LEDs (surface-mount). 2-wire BUS connection.
- **5HV-306**
2W METAL CASE SPEAKER UNIT - Independent digital speaker unit in metal case, with microphone, loudspeaker, emergency button and LEDs.
- **6CV-30022**
MICROPHONE - Soldered on shielded cable L= 3 m.
- **5HV-036**
PASSIVE SPEAKER UNIT - With microphone and loudspeaker.
- **5HV-021**
PASSIVE SPEAKER UNIT WITH CABLE L = 3 m - With microphone, loudspeaker, emergency pushbutton and shielded cable L = 3 m.
- **5HV-103**
STAINLESS-STEEL PANEL WITH PASSIVE SPEAKER UNIT - with microphone, loudspeaker, pushbutton and LEDs with pictograms.

Machine Room Terminals

- **4TS-101**
ST 100L ANALOG TELEPHONE WITH DISPLAY
- **5TE-016**
FLY-LIFT ANALOG TELEPHONE
- **5TE-018**
SLIM ANALOG TELEPHONE with keypad on the receiver.

Accessories

- **5HV-170/1**
INDUCTION LOOP - Communication aid device for hearing-impaired. Comes with inductive wire and amplifier unit.

Helpy 2W-4G.VoLTE installed in the Machine Room

